

Model: Pocket Spectrum Item: 401639



full color LED light in a pocket size package loaded with features. The high quality 96 CRI bi-color light also has 360 RGB colors and 7 lighting effects.

The Smith-Victor Spectrum Pocket is a



Smith-Victor is a division of PromarkBRANDS 1268 Humbracht Circle, Bartlett, IL 60103 U.S.A. 800-348-9862 or 630-830-9200 sales@smithvictor.com | www.smithvictor.com

Controls and Features:



- 1. On/Off Switch 2.Mode Change Button 3. OLED Screen
 - Selection Lever / Push Switch 5. Charger plug port Battery and mount

Specifications:

- CRI: 96
- LED Count: 120 (82W 36RGB)
- LUX @ 3ft: 400
- Dimming: 100~10%
- Variable Color Temp: 2500~7000K
- RGB Colors: 360
- · Power Source: 1, Canon Style LP-E6 Battery
- Battery: 7.4V, 1600mAh
- DC Input: USB Charger
- LED Life Expectancy: 50,000 hrs
- Power Consumption: 10W
- *Approx. 80W Incandescent Equivalent • Fixture Mount: 1/4"-20, Female Thread

Operation:

as the battery level.

1. Install the LP-E6 battery onto the battery mount (6). Check the battery and charge if needed. Charging time for full charge is 2-3 hours.

- 2. Turn on the power switch (1). The OLED (3) will display the color temp and brightness as well
- Press the Selection Lever/Push Switch(4) The > will allow you to select CCT or BRI. Once a selection is made, the setting can be changed by turning the same lever up or down.



CCT 5000 BRI 20% 4. Press the Mode button (2) once and the light

will be in color mode. The hue can be changed using the Selection lever (4). To change the brightness, press the Selection lever/ push switch in until the > points to BRI. The brightness can now be changed with the Selection lever.





5. Press the Mode button(6) again and the light will be in Special Effects mode. Use the Selection lever to toggle through the 7 options. Press the Mode button again and the light returns to white mode.

Contents of the Box:



- (1) LP-E6 Battery
- (1) USB-A to USB-C cord (1) Carry Pouch

Smith-Victor Warranty:

Smith-Victor warrants to the first owner of the Pocket Spectrum to be free from defects in the material and workmanship for a period of one (1) year from the date of purchase and will repair or replace product found to be defective under normal use. Warranty does not cover damages caused by shipment, by product abuse, accident, modification, disassembly or use beyond intended use specified by Smith-Victor. The Pocket Spectrum used with nonstandard Smith-Victor electrical accessories will render this warranty immediately void.

This warranty is the only warranty made to any person by Smith-Victor and is in lieu of all other expressed or implied warranties. The remedies set for this warranty shall be the exclusive remedies available to any person

for breach of this warranty. Under no circumstances shall Smith-Victor be liable to any person for incidental or consequential damages, whether arising out of breach of warranty or other contract, negligence, strict liability or other tort or otherwise